

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 1 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

Table of contents

1.	Objectives / Purpose	4
2.	Scope	4
3.	Document Introduction	4
3.1	Reference	4
3.2	Version History	4
4.	SST Introduction.....	5
4.1	SST Reference.....	5
4.2	Site Reference.....	5
4.3	Site Description	5
5.	Conformance Claim.....	7
6.	Security Problem Definition	8
6.1	Assets.....	8
6.2	Threats	8
6.3	Organizational Security Policies.....	9
6.4	Assumptions.....	9
7.	Security Objectives.....	11
7.1	Security Objectives Rationale	12
8.	Extended Assurance Components Definition	17
9.	Security Assurance Requirements	18
9.1	Application Notes and Refinements	18
9.1.1	CM Capabilities (ALC_CMC.5).....	18
9.1.2	CM Scope (ALC_CMS.5).....	18
9.1.3	Development Security (ALC_DVS.2)	18
9.1.4	Life-cycle Definition (ALC_LCD.1).....	18
9.1.5	Tools and Techniques (ALC_TAT.3).....	19
9.2	Security Requirements Rationale.....	19
9.2.1	Security Requirements Rationale - Dependencies.....	19
9.2.2	Security Requirements Rationale – Mapping.....	19
10.	Site Summary Specification.....	26
10.1	Preconditions required by the Site.....	26
10.2	Services of the Site	27
10.3	Security Assurance Rationale	27
10.3.1	CM capabilities (ALC_CMC.5)	27
10.3.2	CM scope (ALC_CMS.5).....	27
10.3.3	Development Security (ALC_DVS.2)	27
10.3.4	Life-cycle definition (ALC_LCD.1)	27
10.3.5	Tools and techniques (ALC_TAT.3).....	27
10.4	Objectives Rationale	28
10.4.1	O.Physical-Access	28
10.4.2	O.Security-Control.....	28
10.4.3	O.Alarm-Response.....	28

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 2 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

10.4.4	O.Internal-Monitor	28
10.4.5	O.Maintain-Security.....	29
10.4.6	O.Logical-Operation	29
10.4.7	O.Staff-Engagement.....	29
10.4.8	O.Control-Scrap	29
10.4.9	O.Config_Activities.....	30
10.4.10	O.Config_IT-env	30
10.4.11	O.Network_Separation.....	30
10.4.12	O.LifeCycle_doc.....	30
11.	References	31
11.1	Literature	31
11.2	List of Abbreviations	32
11.3	Revision History	32

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 3 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

Table of Figures

Table 1 Threats and OSP - Security Objectives Rationale.....	16
Table 2 Rationale for ALC_CMC.5.....	22
Table 3 Rationale for ALC_CMS.5.....	23
Table 4 Rationale for ALC_DVS.2.....	24
Table 5 Rationale for ALC_LCD.1.....	25
Table 6 Rationale for ALC_TAT.3.....	25

Publication Summary

Reference Number (NXPOMS-ID)	NXPOMS-1719007347-2720
Reference Title	Site Security Target Lite – NXP Munich North
Publisher	Business Unit Security & Connectivity
Classification	Company PUBLIC
Author	Erich Zittlau
Owner	Erich Zittlau
Archive Numbers	See reference number

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 4 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

1. Objectives / Purpose

See chapter 4.

2. Scope

This document is applicable to the following organisation(s): BU Security and Connectivity; Munich

3. Document Introduction

3.1 Reference

Title: Site Security Target Lite – NXP Munich North

Version: 1.0

Date: 3/7/2017

Company: NXP Semiconductors

Name of site: NXP Munich North

EAL: SARs taken from EAL6

3.2 Version History

Version	Date	Comment
V1.0	2017-03-07	first release, based on PV3-00199 V1.4

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 5 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

4. SST Introduction

- 1 The chapters 2 to 9 of this document are based upon the Eurosmart Site Security Target Template [1] with adaptations such that it fits the site (i.e. development site, testing of hardware and software, no production, no direct delivery to customers of the user of the site).
- 2 This Site Security Target is intended to be used by NXP Semiconductors Business Unit Identification (BU S&C).

4.1 SST Reference

- 3 Title Site Security Target Lite – NXP Munich North
- 4 Version 1.0

4.2 Site Reference

- 5 The site belongs to NXP Semiconductors Germany and is located at:

NXP Semiconductors Germany GmbH
Schatzbogen 7
81829 Munich
Germany

4.3 Site Description

- 6 The site as described in section 4.2 is in the scope of the SST.
- 7 The development area is located in the second floor on the north building part, in a closed area and consists of one RED area¹.
- 8 The development area is a security area with restricted access where only authorized persons are allowed to enter this area.
- 9 Within the development area, only members of the development team are entitled to access sensitive information i.e. source code, confidential documentation and samples. To enforce such access restriction, a combination of physical, procedural, personnel and logical measurements have been installed. Note that physical security objects are only allowed to remain unattended in the lab room (separate room with dedicated access control within the RED area).
- 10 The activities are: Security IC Embedded Software Development (Phase 1), IC Embedded Software and Testing (Phase 1), IC Dedicated Software and Testing (Phase 1) as defined in

¹ The terms YELLOW area and RED area are defined in the NXP internal document „NXPOMS-1719007374-2404 BU S&C Security Requirements Overview“; the site specific description can be found in „PV3-00198 Site Security Manual, Munich North“ [10].

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 6 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

‘Security IC Platform Protection Profile’ (PP-0035) and ‘Security IC Platform Protection Profile with Augmentation Packages’ (PP-0084)

11 To perform these activities the site uses the NXP BU S&C provided and managed remote IT-infrastructure. Locally available IT equipment like workstations or VPN routers are also provided and managed by NXP BU S&C directly. The site works according to NXP BU S&C processes.

12 The activities (and areas where they are performed) are:

Activity	Area
Development and testing* of software for secure integrated circuits.	NXP Secure Area
Engineering Test of Software development	NXP Secure Area

* Note that the site of this Site Security Target also belong to NXP BU S&C.

13 The typical Life Cycle model for Smart Cards usually comprises the following phases:

- Development,
- Production,
- Delivery,
- Preparation,
- Operation.

14 Whereas the site under evaluation supports only the life cycle phase

- Development

15 Development comprises of the generation of source code modules and the test of this code only.

16 The site also provides a secure physical environment (RED area) for classified IT infrastructure and equipment installed by NXP BU S&C.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 7 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

5. Conformance Claim

17 This SST is conformant with Common Criteria Version 3.1:

- Common Criteria for Information Technology Security Evaluation, Part 1: Introduction and General Model; Version 3.1, Revision 4, September 2012,
- (Common Criteria, July 2012)Common Criteria for information Technology Security Evaluation, Part 3: Security Assurance Requirements; Version 3.1, Revision 4, September 2012, (Common Criteria, September 2012)

18 For the evaluation, the following methodology will be used:

- Common Methodology for Information Security Evaluation (CEM), Evaluation Methodology; Version 3.1, Revision 4, September 2012, (Common Criteria, September 2012)
- Minimum Site Security Requirement Version 1.1, June 2013 [5]

19 This SST is CC Part 3 conformant.

20 There are no extended components required for this SST for the NXP Munich North Site.

21 The evaluation of the site comprises the following assurance components:

- ALC_CMC.5,
- ALC_CMS.5,
- ALC_DVS.2,
- ALC_LCD.1,
- ALC_TAT.3.

22 The assurance level chosen for the SST is compliant to the Security IC Platform Protection Profile (Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0, 15.06.2007), [7] and is therefore suitable for the evaluation of software and Hardware design for Security ICs.

23 The chosen assurance components are derived from the assurance level EAL6 of the assurance class "Life-cycle Support". For the assessment of the security measures attackers with a high attack potential are assumed. Therefore this site supports potentially augmented product evaluations up to EAL6.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 8 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

6. Security Problem Definition

24 The Security Problem Definition comprises security problems derived from threats against the assets handled by the site.

25 Where necessary the items in this section have been re-worked to fit the site

6.1 Assets

26 The following section describes the assets handled at the site.

Development data: The site has access to (and optionally copies thereof) electronic development data (specifications, guidance documentation, source code, etc.) in relation to developed TOEs. Both the integrity and the confidentiality of these electronic documents must be protected.

Development tools: To perform its development activities the site uses tools (e.g. compiler) to transform source code (and potentially the libraries that come with these tools) into binaries. The integrity of these tools (running on local or remote development computers) must be protected.

Physical security objects: The site has physical security objects (IC samples, printed documents, etc.) in relation to developed TOEs. Both the integrity and the confidentiality of these must be protected.

6.2 Threats

T.Smart-Theft: An attacker tries to access sensitive areas of the site for manipulation or theft of assets.

(1) In this case development data with the intention to violate confidentiality and possibly integrity.

(2) Physical security objects (see 6.1).

(3) Development Tools in the form of IT infrastructure hardware.

The attacker has sufficient time to investigate the site outside the controlled boundary. For the attack the use of standard equipment for burglary is considered.

T.Rugged-Theft: An attacker with specialized equipment for burglary, who may be paid to perform the attack, tries to access sensitive areas and manipulate or steal assets (1) In this case development data with the intention to violate confidentiality and possibly integrity (2) Physical security objects in the form of IC samples and printed documentation (3) Development Tools in the form of IT infrastructure hardware.

T.Computer-Net: A possibly paid hacker with substantial expertise using standard equipment attempts to remotely access sensitive network segments to get

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 9 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

access to (1) development data with the intention to violate confidentiality and possibly integrity or (2) development computers with the intention to modify the development process.

T.Unauthorised-Staff: Employees or subcontractors not authorized to get access to assets by violating (1) In this case development data with the intention to violate confidentiality and possibly integrity (2) Physical security objects in the form of IC samples and printed documentation (3) Development Tools in the form of IT infrastructure hardware.

T.Staff-Collusion: An attacker tries to get access to assets by getting support from one employee through extortion or bribery. (1) In this case development data with the intention to violate confidentiality and possibly integrity (2) Physical security objects in the form of IC samples and printed documentation (3) Development Tools in the form of IT infrastructure hardware.

6.3 Organizational Security Policies

P.Config_IT-env: The site uses software on development workstations and servers in addition to configuration management systems for file versioning and problem tracking. For file versioning unique repositories shall be used to support proper management of multiple products and the site internal procedures and helps meet the objective of (O.Config_IT-env). The team members are instructed to use only project related IT equipment provided by NXP with the provided tools.

P.LifeCycle-Doc: The site uses life cycle documentation that describes:

- (1) Description of configuration management systems and their usage;
- (2) A configuration items list;
- (3) Site security;
- (4) The development process;
- (5) The development tools;
- (6) CM_Plan.

These help meet the objective of O.Lifecycle-Doc

P.Config_Activities: The activities of the site shall be performed in accordance with the life cycle documentation (P.Config_IT-env) and helps meet the objective of (O.Network-separation) using the IT-environment (O.Config_Activities).

6.4 Assumptions

A.Inherit-secure-IT: The local IT equipment (e.g. workstations) is connected to a secure remote IT-Infrastructure through a secure (encrypted) network connection. The local workstations, the remote secure IT-infrastructure and the secure connection to it will satisfy all relevant ALC requirements and are provided

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 10 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

and managed by NXP. The workstations are configured such that any assets are contained within encrypted containers.

A.Setup-Projects: To enable that the site participates in the development of products NXP provides services to setup the necessary development computers (tools, user accounts, etc.) and configuration management systems (user accounts, repositories etc.).

A.Product-Setup: The site participates in the development of products. To define the participation of the site in the development while maintaining quality, for each product NXP will manage the activities to be performed by the site, the specifications of the input for the site and the acceptance of the results by NXP.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 11 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

7. Security Objectives

27 The Security Objectives are related to physical, technical, and organizational security measures, the configuration management as well as the internal shipment and/or the external delivery.

O.Config_IT-env: The site uses software on development workstations and servers in addition to configuration management systems for file versioning and problem tracking. For file versioning unique repositories are used to support proper management of multiple products and the site internal procedures.

O.LifeCycle-Doc: The site uses life cycle documentation that describes:

- (1) Description of configuration management systems and their usage;
- (2) A configuration items list;
- (3) Site security;
- (4) The development process;
- (5) The development tools;
- (6) CM_Plan

O.Config_Activities: The activities of the site are performed in accordance with the life cycle documentation (O.Config_IT-env) using the IT-environment (O.LifeCycle-Doc).

O.Physical-Access: The combination of physical partitioning between the different access control levels together with technical and organisational security measures allows a sufficient separation of employees to enforce the “need to know” principle. The access control shall support the limitation for the access to these areas including the identification and rejection of unauthorised people. The access control measures ensure that only registered employees can access restricted areas. Assets are handled in restricted areas only.

O.Security-Control: Assigned personnel of the site operate the systems for access control. Out of hour surveillance and respond to alarms is contracted to a 3rd party security company. Technical security measures like motion sensors and similar kind of sensors support the enforcement of the access control. NXP personnel are also responsible for registering and ensuring escort of visitors, contractors and suppliers.

O.Alarm-Response: The technical and organisational security measures ensure that an alarm is generated before an unauthorised person gets access to any asset. After the alarm is triggered the unauthorised person still has to overcome further security measures. The reaction time of the employees and/or guards is short enough to prevent a successful attack.

O.Internal-Monitor: The site performs security management meetings at least every six months. The security management meetings are used to review security incidences, to verify that maintenance measures are applied and to

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 12 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

reconsider the assessment of risks and security measures. Furthermore, an internal audit is performed every year to control the application of the security measures.

O.Maintain-Security: Technical security measures are maintained regularly to ensure correct operation. The logging of sensitive systems is checked regularly. This comprises the access control system to ensure that only authorised employees have access to sensitive areas as well as computer/network systems to ensure that they are configured as required to ensure the protection of the networks and computer systems.

O.Network-separation: The (plain-text) development network of the site exists within the secured areas of the site only. It is connected only to:

(1) The encryption equipment employs encrypted VPNs to the secure network provided by the NXP;

(2) The development workstations provided by the NXP;

(3) Additional equipment (e.g. a printer) approved by the NXP.

O.Logical-Operation: Development computers enforce that every user authenticates using a password and has a unique user ID.

O.Control-Scrap: The site has measures in place to either securely destroy assets (e.g. paper shredder) or return them to the NXP for destruction.

O.Staff-Engagement: All employees who have access to assets are checked regarding security concerns and have to sign a non-disclosure agreement. Furthermore, all employees are trained and qualified for their job. All contractors and visitors must be escorted by a trained employee at all times.

7.1 Security Objectives Rationale

28 The SST includes a Security Objective Rationale with two parts. The first part includes the tracing which shows how the threats and OSPs are covered by the Security Objectives. The second part includes a justification that shows that all threats and OSPs are effectively addressed by the Security Objectives (see column "Rationale" of table 1 and Table 2)

29 Note that the assumptions of the SST cannot be used to cover any threat or OSP of the site. They are seen as pre-conditions fulfilled either by the site providing the sensitive configuration items or by the site receiving the sensitive configuration items. Therefore, they do not contribute to the security of the site under evaluation.

Threat and OSP	Security Objective(s)	Rationale
----------------	-----------------------	-----------

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 13 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

T.Smart-Theft	<ul style="list-style-type: none"> O.Lifecycle-Doc O.Physical-Access O.Control-Scrap O.Security-Control O.Alarm-Response O.Internal-Monitor O.Maintain-Security O.Config_Activities 	<p>O.Lifecycle-Doc ensure that procedures are documented which assist in preventing Theft.</p> <p>O.Physical-Access ensures that the Secure Room is physically partitioned off, so that a burglar cannot just walk in.</p> <p>O.Control-Scrap ensures that scrap material cannot be accessed by an authorized party</p> <p>O.Security-Control ensures that an attacker will be detected when trying to reach the assets through the Secure Room</p> <p>O.Alarm-Response supports O.Physical_Access and O.Security_Control by ensuring that a response will be given to the alarm systems and that this response is quick enough to prevent access to the assets.</p> <p>O.Internal-Monitor and O.Maintain-Security ensure that the above is managed and maintained.</p> <p>O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation.</p> <p>Together, these objectives will therefore counter T.Smart_Theft..</p>
T.Rugged-Theft	<ul style="list-style-type: none"> O.Lifecycle-Doc O.Physical-Access O.Control-Scrap O.Security-Control O.Alarm-Response O.Internal-Monitor O.Maintain-Security O.Config_Activities 	<p>O.Lifecycle-Doc ensure that procedures are documented which assist in preventing Theft.</p> <p>O.Physical-Access ensures that the Secure Room is physically partitioned off, so that a burglar cannot just walk in.</p> <p>O.Control-Scrap ensures that scrap material cannot be accessed by an authorized party</p> <p>O.Security-Control ensures that an attacker will be detected when trying to reach the assets through the Secure Room</p> <p>O.Alarm-Response supports O.Physical_Access and O.Security_Control by ensuring that a response will be given to the alarm systems and that this response is quick enough to prevent access to the assets.</p> <p>O.Internal-Monitor and O.Maintain-Security ensure that the above is managed and maintained.</p> <p>O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation.</p> <p>Together, these objectives will therefore counter T.Rugged_Theft</p>



NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 14 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

T.Computer-Net	O.Config_IT-env O.Lifecycle-Doc O.Network-separation O.Physical-Access O.Logical-Operation O.Internal-Monitor O.Maintain-Security O.Control-Scrap O.Staff-Engagement O.Config_Activities	<p>O.Config_IT-env ensures by configuration management segregation of duties and the need to know principals.</p> <p>O.Network-separation ensures that the development network is not connected to anything that an attacker could use to set up a remote connection.</p> <p>O.Physical-Access ensures that all communication between the Secure Room and the Business Unit is done through encryption equipment (provided by the Business Unit). The attacker can therefore neither: Listen in on or manipulate the network connection between the Secure Room and the Business Unit Penetrate the Secure Room management stations through this connection. The attacker also cannot use other networks that lead into the Secure Room as O.Physical-Access also ensures that all such connections are not connected to the encryption equipment.</p> <p>In addition, O.Logical-Operation ensures that all computer systems used to manage the Business Unit network are kept up to date (software updates, security patches, virus and spyware protection).</p> <p>O.Lifecycle-Doc ensure that procedures are documented which assist in preventing Unauthorised Staff access.</p> <p>O.Internal-Monitor and O.Maintain-Security ensure that the above is managed and maintained.</p> <p>O.Control-Scrap ensures that scrap material cannot be accessed by an authorized party.</p> <p>O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation.</p> <p>O.Staff-Engagement ensures that all staff is aware of its responsibilities (signing NDAs, and being trained).</p> <p>Together, these objectives will therefore counter T.Computer-Net.</p>
----------------	---	--



NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 15 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

<p>T.Unauthorised-Staff</p>	<p>O.Physical-Access O.Security-Control O.Alarm-Response O.Internal-Monitor O.Maintain-Security O.Config_IT-env O.Logical-Operation O.Control-Scrap O.Config_Activities O.Network-separation O.Lifecycle-Doc O.Staff-Engagement</p>	<p>O.Security_Control ensures that all unauthorised people who have a legitimate need to visit the Secure Room are always accompanied.</p> <p>O.Physical-Access, O.Security-Control and O.Alarm-Response ensures that the unauthorised people cannot circumvent this (see the rationale for T.Smart-Theft for more details on this).</p> <p>O.Internal-Monitor and O.Maintain-Security ensure that the above is managed and maintained.</p> <p>O.Config_IT-env ensures by configuration management segregation of duties and the need to know principals.</p> <p>O.Control-Scrap ensures that scrap material cannot be accessed by an authorized party.</p> <p>O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation.</p> <p>O.Network-separation ensures that that access can only be gained to networks on a need to know basis.</p> <p>In addition, O.Logical-Operation ensures that all computer systems used to manage the Business Unit network are kept up to date (software updates, security patches, virus and spyware protection).</p> <p>O.Lifecycle-Doc ensure that procedures are documented which assist in preventing Unauthorised Staff access.</p> <p>O.Staff-Engagement ensures that all staff is aware of its responsibilities (signing NDAs, and being trained).</p> <p>Together, these objectives will therefore counter T.Unauthorised-Staff.</p>
-----------------------------	---	--

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 16 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

T.Staff-Collusion	O.Internal-Monitor O.Maintain-Security O.Staff-Engagement O.Config_IT-env O.Control-Scrap O.Config_Activities O.Lifecycle-Doc O.Physical-Access	O.Staff-Engagement ensures that all staff is aware of its responsibilities (signing NDAs, and being trained). O.Internal-Monitor and O.Maintain-Security ensure that the above is managed and maintained. O.Config_IT-env ensures by configuration management segregation of duties and the need to know principals. O.Control-Scrap ensures that scrap material cannot be accessed by an authorized party O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation. O.Lifecycle-Doc ensure that procedures are documented which assist in preventing Unauthorised Staff access. O.Physical-Access ensures need to know access to reduce the risk. Together, these objectives will therefore counter T.Staff-Collusion.
P.Config_IT-env	O.Config_IT-env	The Security Objective directly enforces the OSP. O.Config_IT-env ensures by configuration management segregation of duties and the need to know principals.
P.Config_Activities	O.Config_Activities O.Physical-Access O.Network-separation	The Security Objective directly enforces the OSP. O.Physical-Access ensures need to know access to configuration management systems. O.Config_Activities ensure activities of the site are performed in accordance with the life cycle documentation. O.Network-separation ensures that that access can only be gained to networks on a need to know basis. The services and processes provided by the site are described in the internal procedures and guidance. As these are kept under CM (see the rationale above), this is sufficient to meet P.Config_Activities.
P.LifeCycle-doc	O.LifeCycle-doc	The Security Objective directly enforces the OSP. This ensures life cycle documentation that describes configuration management systems, site security, development process and tools providing a CM_Plan is sufficient to meet P.LifeCycle-doc.

Table 1 Threats and OSP - Security Objectives Rationale

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 17 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

8. Extended Assurance Components Definition

30 No extended components are defined in this Site Security Target.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 18 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

9. Security Assurance Requirements

31 NXP Munich North using this Site Security Target requires a TOE evaluation up to evaluation assurance level EAL6, potentially claiming conformance with the Eurosmart Protection Profile (Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0, 15.06.2007), [7].

32 The Security Assurance Requirements are chosen from the class ALC (Life-cycle support) as defined in (Common Criteria, September 2012):

- CM capabilities (ALC_CMC.5)
- CM scope (ALC_CMS.5)
- Development Security (ALC_DVS.2)
- Life-cycle definition (ALC_LCD.1)
- Tools and techniques (ALC_TAT.3)

33 Because hierarchically higher components are used in this SST the Security Assurance Requirements listed above fulfil the requirements of:

- [5] 'Minimum Site Security Requirements'
- (Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0, 15.06.2007), [7] Eurosmart Security IC Platform Protection Profile.

34 In addition, SAR as defined [5] 'Minimum Site Security Requirements' is augmented by assurance components from 'Life-cycle definition' (ALC_LCD.1) and 'Tools and techniques' (ALC_TAT.3).

9.1 Application Notes and Refinements

35 The description of the site certification process [8] includes specific application notes. The main item is that a product that is considered as intended TOE is not available during the evaluation. Since the term "TOE" is not applicable in the Site Security Target, the associated processes for the handling of products, or "intended TOEs" are in the scope of this Site Security Target and are described in this document. These processes are subject of the evaluation of the site.

9.1.1 CM Capabilities (ALC_CMC.5)

36 Refer to subsection 'Application Notes for Site Certification' in [8] 5.1 'Application Notes for ALC_CMC'.

9.1.2 CM Scope (ALC_CMS.5)

37 Refer to subsection 'Application Notes for Site Certification' in [8] 5.2 'Application Notes for ALC_CMS'.

9.1.3 Development Security (ALC_DVS.2)

38 Refer to subsection 'Application Notes for Site Certification' in [8] 5.4 'Application Notes for ALC_DVS'.

9.1.4 Life-cycle Definition (ALC_LCD.1)

39 Refer to subsection 'Application Notes for Site Certification' in [8] 5.6 'Application Notes for ALC_LCD'.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 19 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

- 40 Refer to ‘*Application Note 26*’ in 6.2.1.2 ‘Refinements regarding Development Security (ALC_DVS)’ in the Eurosmart PP (Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0, 15.06.2007).
- 41 Refer to subsection ‘*Refinement*’ in 6.2.1.2 ‘Refinements regarding Development Security (ALC_DVS)’ in the Eurosmart PP (Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0, 15.06.2007).
- 42 Refer to subsection “C Excerpts from the Criteria in Security assurance components (chapter 7)” in [12] Security IC Platform Protection Profile (BSI-CC-PP-0084-2014), Version 1.0, Eurosmart, 2014 [7].

9.1.5 Tools and Techniques (ALC_TAT.3)

- 43 Refer to subsection ‘Application Notes for Site Certification’ in [8] 5.7 ‘Application Notes for ALC_TAT’.

9.2 Security Requirements Rationale

9.2.1 Security Requirements Rationale - Dependencies

44 The dependencies for the assurance requirements are as follows:

- ALC_CMC.5: ALC_CMS.1, ALC_DVS.2, ALC_LCD.1
- ALC_CMS.5: None
- ALC_DVS.2: None
- ALC_LCD.1: None
- ALC_TAT.3: ADV_IMP.1
-

45 Some of the dependencies are not (completely) fulfilled:

- ALC_LCD.1 is only partially fulfilled as the site does not represent the entire development environment. This is in-line with and further explained in [8] 5.1 ‘Application Notes for ALC_CMC’.
- ADV_IMP.1 is not fulfilled as there is no specific TOE. This is in-line with and further explained in [8] 5.7 ‘Application Notes for ALC_TAT’.

9.2.2 Security Requirements Rationale – Mapping

SAR	Security Objective	Rationale
ALC_CMC.5.1C: The CM documentation shall show that a process is in place to ensure an appropriate and consistent labeling.	O.Config_IT-env O.LifeCycle-Doc O.Config_Activities	Appropriate and consistent labelling is ensured through the application (O.Config_Activities) of the CM-Plan (O.LifeCycle-Doc) and the use of the configuration management systems (O.Config_IT-env).

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 20 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
ALC_CMC.5.2C: The CM documentation shall describe the method used to uniquely identify the configuration items.	O.LifeCycle-Doc	The method used to uniquely identify the configuration items is described in the CM-Plan (O.LifeCycle-Doc).
ALC_CMC.5.3C: The CM documentation shall justify that the acceptance procedures provide for an adequate and appropriate review of changes to all configuration items.	O.LifeCycle-Doc	The adequate and appropriate acceptance procedures for configuration items are described in the CM-Plan (O.LifeCycle-Doc).
ALC_CMC.5.4C: The CM system shall uniquely identify all configuration items.	O.Config_IT-env O.LifeCycle-Doc O.Config_Activities	Unique identification of all CIs is realized by performing the CM activities (O.Config_Activities) in accordance with the CM-Plan (O.LifeCycle-Doc) using the Configuration management systems (O.Config_IT-env)
ALC_CMC.5.5C: The CM system shall provide automated measures such that only authorized changes are made to the configuration items.	O.Config_IT-env O.LifeCycle-Doc O.Config_Activities	The configuration management systems (O.Config_IT-env) used (O.Config_Activities) according to the CM-Plan (O.LifeCycle-Doc) enforces automated measures such that only authorized changes are made to the configuration items
ALC_CMC.5.6C: The CM system shall support the production of the product by automated means.	O.Config_IT-env O.LifeCycle-Doc O.Config_Activities	The software on the development computers (O.Config_IT-env) supports automated production of products when used (O.Config_Activities) in accordance with the CM-Plan (O.LifeCycle-Doc)
ALC_CMC.5.7C: The CM system shall ensure that the person responsible	O.LifeCycle-Doc O.Config_Activities	As described in the CM-Plan (O.LifeCycle-Doc) the activities performed (O.Config_Activities) are such

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 21 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
for accepting a configuration item into CM is not the person who developed it.		that the person responsible for accepting a configuration item into CM is not the person who developed it.
ALC_CMC.5.8C: The CM system shall clearly identify the configuration items that comprise the TSF.	O.Config_IT-env O.LifeCycle-Doc	The CM-Plan (O.LifeCycle-Doc) identifies the configuration items that comprise the TSF possibly supported by the configuration management system (O.Config_IT-env)
ALC_CMC.5.9C: The CM system shall support the audit of all changes to the TOE by automated means, including the originator, date, and time in the audit trail.	O.Config_IT-env O.LifeCycle-Doc	As described in the CM_Plan (O.LifeCycle-Doc) the configuration management systems (O.Config_IT-env) are configured such that an audit trail (showing originator, date and time) is automatically generated.
ALC_CMC.5.10C: The CM system shall provide an automated means to identify all other configuration items that are affected by the change of a given configuration item.	O.Config_IT-env O.LifeCycle-Doc	As described in the CM_Plan (O.LifeCycle-Doc) the configurations management system and software installed on the development workstations and servers (O.Config_IT-env) provide automated means to identify all other configuration items that are affected by the change of a given configuration item.
ALC_CMC.5.11C: The CM system shall be able to identify the version of the implementation representation from which the TOE is generated.	O.Config_IT-env O.LifeCycle-Doc	As described in the CM_Plan (O.LifeCycle-Doc) the configurations management system (O.Config_IT-env) identifies the version of the implementation representation from which the TOE is generated through baselines.
ALC_CMC.5.12C: The CM documentation shall include a CM plan.	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) includes a CM-Plan.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 22 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
ALC_CMC.5.13C: The CM plan shall describe how the CM system is used for the development of the TOE.	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) describes how the CM system is used for the development of the product.
ALC_CMC.5.14C: The CM plan shall describe the procedures used to accept modified or newly created configuration items as part of the TOE	O.LifeCycle-Doc	The acceptance procedures for modified or newly created configuration items are described in the CM-Plan (O.LifeCycle-Doc).
ALC_CMC.5.15C: The evidence shall demonstrate that all configuration items are being maintained under the CM system.	O.LifeCycle-Doc	All configuration items are listed in the CI-list (O.LifeCycle-Doc)
ALC_CMC.5.16C: The evidence shall demonstrate that all configuration items have been and are being maintained under the CM system.	O.Config_IT-env O.LifeCycle-Doc	The CI-list (O.LifeCycle-Doc) is generated from the configuration management systems (O.Config_IT-env)

Table 2 Rationale for ALC_CMC.5

SAR	Security Objective	Rationale
ALC_CMS.5.1C: The configuration list includes the following: the TOE itself; the evaluation evidence required by the SARs in	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) includes a CM-Plan and a CI-List with the items required by ALC_CMS.5.1C

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 23 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
the ST; the parts that comprise the TOE; the implementation representation; security flaws; and development tools and related information. The CM documentation shall include a CM plan.		
ALC_CMS.5.2C: The configuration list shall uniquely identify the configuration items.	O.LifeCycle-Doc	The CI-List (O.LifeCycle-Doc) uniquely identifies the configurations items as described in the CM-Plan (O.LifeCycle-Doc).
ALC_CMS.5.3C: For each configuration item, the configuration list shall indicate the developer/subcontractor of the item.	O.LifeCycle-Doc	The CI-List (O.LifeCycle-Doc) indicates the developer/subcontractor for each configuration items as described in the CM-Plan (O.LifeCycle-Doc).

Table 3 Rationale for ALC_CMS.5

SAR	Security Objective	Rationale
ALC_DVS.2.1C: The development security documentation shall describe all the physical, procedural, personnel, and other security measures that are necessary to protect the confidentiality and integrity of the TOE design and implementation in its development environment.	O.LifeCycle-Doc O.Physical-Access O.Security-Control O.Alarm-Response O.Internal-Monitor O.Maintain-Security O.Network-separation O.Logical-Operation O.Control-Scrap	The development security documentation (O.LifeCycle-Doc) describes the physical (O.Physical-Access, O.Security-Control, O.Alarm-Response), procedural (O.Internal-Monitor, O.Maintain-Security, O.Control-Scrap), personnel (O.Staff-Engagement), and other (O.Network-separation, O.Logical-Operation) security measures that are necessary to protect the confidentiality and integrity of the TOE

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 24 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
	O.Staff-Engagement	design and implementation in its development environment.
ALC_DVS.2.2C: The development security documentation shall justify that the security measures provide the necessary level of protection to maintain the confidentiality and integrity of the TOE.	O.LifeCycle-Doc	The development security documentation (O.LifeCycle-Doc) justifies the security measures provide the necessary level of protection to maintain the confidentiality and integrity of the TOE.
ALC_DVS.2.3C: The evidence shall justify that the security measures provide the necessary level of protection to maintain the confidentiality and integrity of the TOE.	O.LifeCycle-Doc O.Physical-Access O.Security-Control O.Internal-Monitor O.Maintain-Security O.Network-separation O.Logical-Operation O.Control-Scrap O.Staff-Engagement	The development security documentation (O.LifeCycle-Doc) describes the physical (O.Physical-Access, O.Security-Control), procedural (O.Internal-Monitor, O.Maintain-Security, O.Control-Scrap), personnel (O.Staff-Engagement), and other (O.Network-separation, O.Logical-Operation) security measures that are necessary to protect the confidentiality and integrity of the TOE design and implementation in its development environment.

Table 4 Rationale for ALC_DVS.2

SAR	Security Objective	Rationale
ALC_LCD.1.1C: The life-cycle definition documentation shall describe the model used to develop and maintain the TOE.	O.LifeCycle-Doc	The model used to develop the TOE is described in the life cycle documentation (O.LifeCycle-Doc)
ALC_LCD.1.2C: The life-cycle model shall provide for the necessary control over the development and	O.LifeCycle-Doc	The life cycle model as described in the life cycle documentation (O.LifeCycle-Doc) provides for the necessary control over the

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 25 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

SAR	Security Objective	Rationale
maintenance of the TOE.		development and maintenance of the TOE.

Table 5 Rationale for ALC_LCD.1

SAR	Security Objective	Rationale
ALC_TAT.3.1C: Each development tool used for implementation shall be well-defined.	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) shows that the development tools used for implementation are well-defined.
ALC_TAT.3.2.C: The documentation of each development tool shall unambiguously define the meaning of all statements as well as all conventions and directives used in the implementation.	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) together with the documentation of the development tools unambiguously defines the meaning of all statements as well as all conventions and directives used in the implementation.
ALC_TAT.3.3C: The documentation of each development tool shall unambiguously define the meaning of all implementation-dependent options.	O.LifeCycle-Doc	The life cycle documentation (O.LifeCycle-Doc) together with the documentation of the development tools unambiguously defines the meaning of all implementation-dependent options.

Table 6 Rationale for ALC_TAT.3

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 26 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

10. Site Summary Specification

10.1 Preconditions required by the Site

- 46 The site activities are performed using an IT infrastructure consisting of development workstations, servers and configuration management systems. All of these are provided, configured and maintained by the NXP.
- 47 The IT infrastructure consists of local and remote equipment connected using an encrypted connection. NXP provides, configures and maintains the local workstations and router (used for the encrypted connection) and all remote equipment such that they are secure. The workstations are configured such that any assets are contained within encrypted containers.
- 48 In case of necessary updates to the life cycle documentation NXP will co-ordinate, communicate and deliver.
- 49 To enable that the site participates in the development and test of products NXP provides services to setup the necessary development computers (tools, user accounts, etc.) and configuration management systems (user accounts, repositories etc.).
- 50 To enable the site to realize shipment such that assurance of integrity is assured throughout transport of physical security objects NXP will manage the shipment method.
- 51 In case the site is unable to securely destroy certain physical assets the assets will be securely stored and shipped to NXP Semiconductors Hamburg for destruction.
- 52 To define the participation of the site in the development while maintaining quality, for each product NXP will manage the activities to be performed, the specifications of the input for the site and the acceptance of the results.
- 53 The site follows the development processes of NXP. Applicable policies and processes are documented and available.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 27 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

10.2 Services of the Site

54 The site participates in the development and test of software for secure integrated circuits.

10.3 Security Assurance Rationale

10.3.1 CM capabilities (ALC_CMC.5)

55 Configuration Management is described in (BU Security & Connectivity ALC-CM - Common Criteria Documentation, NXPOMS-1719007347-2549, 22.12.2016), [10] and [11].

56 For full detail and evidences please view Section 7.2.2

10.3.2 CM scope (ALC_CMS.5)

57 Configuration Management is described in (BU Security & Connectivity ALC-CM - Common Criteria Documentation, NXPOMS-1719007347-2549, 22.12.2016), [10] and [11].

58 For full detail and evidences please view Section 7.2.2

10.3.3 Development Security (ALC_DVS.2)

59 Development Security is described in [10]

60 For full detail and evidences please view Section 7.2.2

10.3.4 Life-cycle definition (ALC_LCD.1)

61 Life-cycle definition is described in (BU Security & Connectivity ALC-CM - Common Criteria Documentation, NXPOMS-1719007347-2549, 22.12.2016) and [10].

62 For full detail and evidences please view Section 7.2.2

10.3.5 Tools and techniques (ALC_TAT.3)

Tools and techniques is described in (BU Security & Connectivity ALC-CM - Common Criteria Documentation, NXPOMS-1719007347-2549, 22.12.2016).

63 For full detail and evidences please view Section 7.2.2

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 28 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

10.4 Objectives Rationale

64 The following rationale provides a justification that shows that all threats and OSP are effectively addressed by the Security Objectives.

10.4.1 O.Physical-Access

65 The NXP Office area is surrounded by a solid wall construction and controlled by Access Control and CCTV. The access to the building is only possible via access reception desk and controlled doors. NXP manages its own dedicated alarm system and the additional external control are graduated according to the running operation at the site. The physical, technical and organizational security measures ensure a separation of the site into three security levels. The access control ensures that only registered persons can access sensitive areas. This is supported by O.Security-Control that includes the maintenance of the access control and the control of visitors. The physical security measures are supported by O.Alarm-Response providing an alarm system.

66 Thereby the threats T.Smart-Theft, T.Rugged-Theft can be prevented. The physical security measures together with the security measure provided by O.Security-Control enforce the recording of all actions. Thereby also T.Computer-Net, T.Staff-Collusion and T.Unauthorized-Staff is addressed. Also addresses the OSP P.Config-Activities.

10.4.2 O.Security-Control

67 During off hours the alarm system is monitored with a dedicated off site monitoring station. The CCTV system supports these measures because it is always enabled. Further on the security control is supported by O.Physical-Access requiring different level of access control for the access to security product during operation as well as during off-hours.

68 This addresses the threats T.Smart-Theft and T.Rugged-Theft. Supported by O.Maintain-Security and O.Physical-Access also an internal attacker triggers the security measures implemented by O.Security-Control. Therefore also the Threat T.Unauthorized-Staff is addressed.

10.4.3 O.Alarm-Response

69 During working hours the employees monitor the alarm system. The alarm system is connected to a control center that is manned 24 hours. During off-hours additional guard patrol supports the alarm system. O.Physical-Access requires certain time to overcome the different level of access control. The response time of the guard and the physical resistance match to provide an effective alarm response.

70 This addresses the threats T.Smart-Theft, T.Rugged-Theft and T.Unauthorised-Staff.

10.4.4 O.Internal-Monitor

71 Regular security management meetings are implemented to monitor security incidences as well as changes or updates of security relevant systems and processes. This comprises of all security events, security relevant systems, CCTV and access control. Major changes of security systems and security procedures are reviewed in general management systems review meetings (4x per year). Upon introduction of a new process a formal review and release for mass production is made before being generally introduced.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 29 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

- 72 The security relevant systems enforcing or supporting O.Physical-Access, O.Security-Control and O.Logical-Access are checked and maintained regularly by the suppliers. In addition the configuration is updated as required either by employees (for the access control system) of the supplier. Logging files are checked at least monthly for technical problems and specific maintenance requests
- 73 This addresses T.Smart-Theft, T.Rugged-Theft, T.Computer-Net, T.Unauthorised-Staff and T.Staff-Collusion
- 10.4.5 O.Maintain-Security
- 74 The security relevant systems enforcing or supporting O.Physical-Access, O.Security-Control and O.Logical-Access are checked and maintained regularly by the suppliers. In addition the configuration is updated as required either by employees (for the access control system) of the supplier. Logging files are checked at least monthly for technical problems and specific maintenance requests.
- 75 These security measures are necessary to prevent the threats T.Smart-Theft, T.Rugged-Theft, T.Computer-Net, T.Unauthorised-Staff and T.Staff-Collusion
- 10.4.6 O.Logical-Operation
- 76 All logical protection measures are maintained and updated as required, at least once a month. Critical items such as virus scanners are updated daily. The backup is sufficiently protected and is only accessible for the administration.
- 77 This addresses the threats T.Computer-Net and T.Unauthorised-Staff
- 10.4.7 O.Staff-Engagement
- 78 All employees are interviewed before hiring. They must sign an NDA and a code of conduct for the use of NXP equipment before they start working in the company. The formal training and qualification includes security relevant subjects and the principles of handling and storage of security products. The security objectives O.Physical-Access, O.Logical- Access and O.Config-Items support the engagement of the staff.
- 79 This addresses the threats T.Computer-Net, T.Staff-Collusion and T.Unauthorised-Staff
- 10.4.8 O.Control-Scrap
- 80 Scrap may only exist in two forms on this site printed secure objects or redundant hardware/movable media. Hardware scrap is returned to NXP Hamburg for controlled secure destruction. Transport and actual destruction of security products is done under supervision of a qualified employee in collaboration with the destructor. Sensitive information and information storage media are collected internally in a safe location and destructed in a supervised and documented process. All documentation destroyed on site is by means of a Level 5 security shredder.
- 81 Supported by O.Physical-Access and O.Staff-engagement this addresses the threats T.Unauthorised-Staff, T.Computer-Net, T.Smart-Theft, T.Rugged-Theft and T.Staff-Collusion.

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 30 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

10.4.9 O.Config Activities

82 All product configuration information is stored in the database on the NXP secure network. The information stored is covering process specifications, acceptance test instructions and specifications, and test programs. Products are identified by unique customer part IDs with are linked to the unique ID numbers of the associated configuration items.

83 This is addressing the threat T.Rugged-Theft, T.Computer-Net, T.Staff-Collusion, T.Unauthorised-Staff, T.Smart-Theft and the OSP P.Config-Activities

10.4.10 O.Config IT-env

84 The configuration of the IT environment is designed in such way to ensure segregation of duties and the need to know principals.

85 These measures address T.Computer-Net, T.Staff-Collusion and T.Unauthorized-Staff. Also addresses the OSP P.Config-IT-env.

10.4.11 O.Network Separation

86 The internal network is separated from the internet with a firewall. The internal network is further separated into subnetworks by internal firewalls. These firewalls allow only authorized information exchange between the internal subnetworks. Each user is logging into the system with his personalised user name and password. The objective is supported by O.Internal-Monitor based on the checks of the logging regarding security relevant events.

87 The individual accounts are addressing T.Computer-Net. All network configuration is stored in the database of the NXP secure network. Supported by O.Config-IT-env this addresses the threats T.Unauthorised-Staff and the OSP P.Config-Activity.

10.4.12 O.LifeCycle doc

88 The security of the site is maintained according to the sites security documentation covering all physical and logical measures to ensure the security of the site.

89 These security measures are necessary to prevent the threats T.Smart-Theft, T.Rugged-Theft, T.Computer-Net, T.Unauthorised-Staff and T.Staff-Collusion. Also addressing the OSP P.Lifecycle-Doc

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 31 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

11. References

11.1 Literature

- [1] "Site Security Target Template, Version 1.0, published by Eurosmart," Eurosmart, 21.06.2009.
- [2] Common Criteria, "Common Criteria for Information Technology Security Evaluations, Part 1: Introduction and General Model; Version 3.1, Revision 4," July 2012.
- [3] Common Criteria, "Common Criteria for Information Technology Security Evaluation, Part3: Security Assurance Requirements; Version 3.1, Revision 4," September 2012.
- [4] Common Criteria, "Common Methodology for Information Technology Security Evaluation (CEM), Evaluation Methodology; Version 3.1, Revision 4," September 2012.
- [5] "Minimum Site Security Requirement, Version 1.1," July 2013.
- [6] "Security IC Platform Protection Profile (BSI-CC-PP-0035-2007), Version 1.0," Eurosmart, 15.06.2007.
- [7] "Security IC Platform Protection Profile with Augmented Packages (BSI-CC-PP-0084-2014), Version 1.0," Eurosmart, 2014.
- [8] Common Criteria, "Supporting Document, Site Certification, Version 1.0, Revision 1, CCDB-2007-11-001," October 2007.
- [9] "BU Security & Connectivity ALC-CM - Common Criteria Documentation, NXPOMS-1719007347-2549," Business Unit Security & Connectivity, 22.12.2016.
- [10] "Site Security Manual - Munich North, PV3-00198, Version 1.1," Business Unit Security & Connectivity, 09.02.2017.
- [11] "NXP Munich North Configuration List".

NXP Semiconductors	Site Security Target Lite – NXP Munich North	Published
Product Creation		3/7/2017
BU Security and Connectivity		Page 32 of 32
Doc. Identifier: NXPOMS-1719007347-2720		Old System Identifier: PV3-00199a

11.2 List of Abbreviations

CC	Common Criteria
EAL	Evaluation Assurance Level
IC	Integrated Circuit
IP	Intellectual Property
IT	Information Technology
OSP	Organizational Security Policy
PP	Protection Profile
SAR	Security Assurance Requirement
SST	Site Security Target
ST	Security Target
TOE	Target of Evaluation

11.3 Revision History

Document Author	Date	Description of Change	Document Owner
Erich Zittlau	3/7/2017	First version (based on PV3-00199 V1.4)	Erich Zittlau
In case of questions or change proposals please contact the latest document author or owner.			

Approvers:

Approvers

Sequence	Role	Name
Acceptance	Security Manager BU S&C	Dirk Lützelberger
Approval	Site Security Munich North	Rainer Dinkel